

## **Line feed boxes Click Ductor**

#### **Product information**

#### General:

Lines feed boxes are used for the connection of the feeder cable on any random point of the system. The feeder cable, connected to line feed clamps, is kept in place by the line clamp holder that partly slides over the 2 housing parts in which up to 7 line feed clamps can be fitted. Basis of all the line feed boxes is the modular collar that is equipped with push through holes to fit various glands M32 to M63 in size. For custom configurations, you can easily add glands by removing the pre-cut sections. The line feed clamp holder (LCH) connects 2 adjacent rail housings and holds the line feed clamps at the same time. Then the line feed clamps are connected to a power cable. Cover comes over the collars and clicks into position.

#### Line feed boxes types LB:

#### Type LB40

Line feed box for connection of copper conductors up to 125A. With 1 gland M40 for cables Ø16-Ø28 mm.

#### Type LB63

Line feed box for connection of copper conductors up to 160A. With 1 gland M63 for cables Ø30-Ø44,5 mm.

#### Type LB32-4

Similar to LB63, with 4 glands M32 for cables Ø10-Ø21 mm.

#### Type LB32-7

Similar to LB32-4, with 7 glands M32 for cables Ø10-Ø21 mm.


#### Line feed clamp holders:


#### Type RC-LCH


Applicable for line feed connections with continuous copper (all sizes), irrespective the number of poles. When mounting, the line feed clamp holder (2 halves) clamps over 2 adjacent rail housings with the line feed clamps already fitted to the copper conductors. See figure. The required line feed clamps have to be ordered separately.

Description	Imax (80% DC) non-parallel (A)	outer diameter feeding cable Ø mm	max. number of copper conductors	Imax (80% DC) parallel switched (A)	IP - class excl. AS7 sealing	IP - class incl. AS7 sealing
Line feed box LB40 1xM40	125	16-28	4xCU125 / 7xCU80	-	IP23	IP44
Line feed box LB63 1x M63	160	30-44	4xCU160 / 7xCU125	250	IP23	IP44
Line feed box LB32-4 4xM32	160	4x 10-21	4xCU160	-	IP23	IP44
Line feed box LB32-7 7xM32	2 173	7x 10-21	7xCU200	346	IP23	IP44
Line feed box LB	-	no glands	-	-	IP23	IP44
Line feed clamp holder RC- LCH	-	-	-	-	IP23	IP44

# Blueprint







### RC-LCH

